

[Back To The Home Page](#)

This "mirrored" page is published through the kind permission of MIX Magazine and PRIMEDIA Business Magazines & Media.

Visit MIX Magazine's WEB Site at: <http://www.mixonline.com>

[Mail A Link To This Page To A Friend!](#)

[Download](#) A Printer-Ready Copy Of This Review. You'll Need A [Free Acrobat PDF Viewer Plug-In](#) For Your Browser.

[Click On The Image Below To Return To The Mix Directory](#)



The Crane Song Trakker is a single-channel, all-Class-A analog compressor-limiter that uses all discrete components in the signal path. Housed in a single-rackspace steel-and-aluminum chassis, the unit has transformerless input and outputs and operates on AC mains voltages from 100 to 240. The Trakker uses Pulse Width Modulation to derive a control signal for the gain changing element--in this case, a Field-Effect Transistor or FET.

Digital control through PWM is not new, and neither is the use of gain-changing FETs: The '60s vintage EMT 156 Stereo Compressor/Limiter is an example of a PWM-controlled processor and the revered UREI 1176LN is a good example of an FET-based peak limiter. The technique of converting an analog waveform into a digital pulse train (A/D conversion) for use as a control voltage has two distinct advantages: Once digital, the control signal can be easily manipulated, and in ways not always possible with analog circuitry. Second, the quality of the analog signal path remains pristine from input to output. In the case of the Crane Song Trakker, a pair of parallel FETs, responding to the PWM sidechain control signal, control the audio output by shunting the output audio to ground. This is the same way a resistive passive volume control works--the most neutral-sounding gain reduction circuit available.

PWM CONTROL

Trakker designer Dave Hill has studied the properties of various newer and vintage compressors and has developed a set of PWM algorithms that emulate four different basic compressor types: Hard Knee, Soft Knee, Optical and Air-Optical. In addition to the four

compressor types, there are four amplifier/modulation styles available that further modulate the compressor's action: Clean, Vintage, Clean VCA and Vintage VCA. These tone coloration circuits add further processing to the PWM control signal and are selected by a 16-position rotary Character switch, divided into four quadrants. Each quadrant is further subdivided into the four amplifier/styles and selections are indicated by a different colored LED. Winding through sixteen positions on the Character switch reveals a relay that creates a slight delay between settings (.2 ms). Once you have decided which compressor type and amplifier/style you would like to use, the unit behaves and works like any another compressor that includes adjustable Attack, Release, Threshold and Knee (Slope or Ratio) controls. The big feature here is that if you change your mind or if a change in the music no longer fits the compressor/amp style you've chosen, you don't have to find and repatch in a different compressor, you just select another compressor type/amplifier style with the Character switch.

COMPRESSOR TYPES


The Hard Knee setting can be thought of as a limiter. When using this mode I had to re-adjust the Knee control (ratio) as well as both the Attack and Release controls. If you like to squash and spank audio, this is the best and most controllable device for it that I have seen. I found all the grit and graininess I could ever need, without having to worry about quality of the audio path suffering. Soft Knee offers a kinder, gentler sound, much like the OverEasy mode in a dbx 160SL. I found that Soft Knee worked better as a music program processor than it did on most individual instrument tracks. With the Optical mode you'll get a more program-dependent action: The release time increases the longer the signal is present. Air-Optical is the same as Optical except for a high-frequency boost; this emulates the way some vintage tube compressors "build in" a high-frequency tilt to maintain an overall flat response (one of the reasons certain vintage gear sounds so wonderful as soon as you patch it in). Switching between Optical and Air-Optical didn't require any re-adjustment, and the sound is a tinge more open in Air-Optical. I used Air-Optical for vocals and Optical for bass guitar and synths.

AMPLIFIER/STYLES

The Amplifier/Style types start with Clean or Transparent, the cleanest mode of the Trakker. This takes full advantage of the discrete Class A audio path. Vintage has the sound of an old triode tube circuit or old-style solid-state Class A--coloration is mostly secondharmonic, with the third harmonic coming in the closer to clip you run the unit. With some vintage tube and solid-state compressors, during gain changing, there is some feed-through of the control voltage that introduces modulating artifacts to the finished sound. These artifacts are mostly heard when fast attack and release settings are used. This is called VCA on the Trakker, and it can be added to either the Clean or the Vintage styles (hence the names Vintage VCA and Clean VCA). The VCA setting introduces dynamic harmonic content change or transit harmonic distortion; the sound becomes thicker while the gain is changing. This is done to keep the audio path of the highest quality. The amplifier styles are easiest to hear in Hard Knee mode, as these qualities come out more when a compressor is working hard. I found the Vintage style very good for vocals and guitars. The Clean style was better for bass and program material, and VCA seems better for drums and percussion.

[Click Here To Return To The Mix Directory](#)

This Review Is Copyright © 1995 Through By [PRIMEDIA Business Magazines & Media](#) All Rights Reserved.



[Back To Home Page](#)

[Back Up To The Top](#) 

[All Web Page Design Is Copyright © 1995 through By Barry Rudolph](#)